


# Metal Regulators with Recessed Adjustment

## 7130 Flow Regulator, Exhaust, Male BSPP and Metric Thread



Nickel-plated brass, NBR




ØD	C		E	F	H	J	L	kg
4	M5x0.8	<a href="#">7130 04 19</a>	4	8	17	9	19	0.015
	G1/8	<a href="#">7130 04 10</a>	5	13	34	15	20	0.037
6	M5x0.8	<a href="#">7130 06 19</a>	4	8	17	9	24	0.013
	G1/8	<a href="#">7130 06 10</a>	5	13	34	15	22	0.038
8	G1/4	<a href="#">7130 06 13</a>	8	17	39	18	24	0.062
	G1/8	<a href="#">7130 08 10</a>	5	13	34	15	25	0.042
8	G1/4	<a href="#">7130 08 13</a>	8	17	39	18	28	0.066
	G3/8	<a href="#">7130 08 17</a>	7	20	47	21.5	29	0.109
10	G1/4	<a href="#">7130 10 13</a>	8	17	39	18	30	0.075
	G3/8	<a href="#">7130 10 17</a>	7	20	47	21.5	32	0.120
10	G1/2	<a href="#">7130 10 21</a>	8	23	61	28	34	0.222
	G3/8	<a href="#">7130 12 17</a>	7	20	47	22	36	0.064
12	G1/2	<a href="#">7130 12 21</a>	8	23	61	28	38	0.306

## 7140 Flow Regulator, Exhaust, Male/Female BSPP and Metric Thread



Nickel-plated brass, NBR




C		E	E1	F	H	J	L	kg
M5x0.8	<a href="#">7140 19 19</a>	4	4	8	21	9	11	0.009
G1/8	<a href="#">7140 10 10</a>	5	8	13	32	15	17	0.040
G1/4	<a href="#">7140 13 13</a>	8	12	17	39	18	24	0.073
G3/8	<a href="#">7140 17 17</a>	7	12	20	47	21.5	27	0.125
G1/2	<a href="#">7140 21 21</a>	8	15	23	61	28	31	0.238

## 7160 Flow Regulator with Brass Compression Fitting, Exhaust, Male BSPP Thread



Nickel-plated brass, NBR



ØD	C		F	F1	H	J	L	L1	kg
4	G1/8	<a href="#">7160 04 10</a>	13	10	26	17	25.5	14.5	0.049
	G1/8	<a href="#">7160 06 10</a>	13	13	26	17	25.5	14.5	0.054
6	G1/4	<a href="#">7160 06 13</a>	17	13	31.5	22	28.5	17.5	0.103
	G1/8	<a href="#">7160 08 10</a>	13	14	26	17	29.5	15.5	0.055
8	G1/4	<a href="#">7160 08 13</a>	17	14	31.5	22	31	17	0.103
	G1/4	<a href="#">7160 10 13</a>	17	19	31.5	22	35	19	0.118
10	G3/8	<a href="#">7160 10 17</a>	20	19	44.5	22	37.5	19	0.188
	G1/2	<a href="#">7160 10 21</a>	23	19	50	27	37.5	19	0.202
12	G3/8	<a href="#">7160 12 17</a>	20	22	44.5	22	38	21.5	0.200
	G1/2	<a href="#">7160 12 21</a>	23	22	50	27	38	21.5	0.213