







# Stainless Steel Adaptors




## 1855 Equal Connector, Female BSPP Thread

	Stainless steel 316L 	<b>C</b>		<b>F</b>	<b>L</b>	<b>kg</b>
		G1/8	<a href="#">1855 10 10</a>	14	17	0.013
		G1/4	<a href="#">1855 13 13</a>	17	24	0.024
		G3/8	<a href="#">1855 17 17</a>	22	25	0.042
		G1/2	<a href="#">1855 21 21</a>	27	32	0.078
		G3/4	<a href="#">1855 27 27</a>	14	35	0.102
		G1	<a href="#">1855 34 34</a>	41	40	0.202




## 1870 Equal Connector, Female NPT Thread

	Stainless steel 316L 	<b>C</b>		<b>F</b>	<b>L</b>	<b>kg</b>
		NPT1/8	<a href="#">1870 11 11</a>	14	19	0.015
		NPT1/4	<a href="#">1870 14 14</a>	17	28	0.029
		NPT3/8	<a href="#">1870 18 18</a>	22	28	0.050
		NPT1/2	<a href="#">1870 22 22</a>	27	35	0.093




## 1862 Reducer Connector, Female BSPP Thread

	Stainless steel 316L 	<b>C1</b>	<b>C2</b>		<b>F</b>	<b>L</b>	<b>kg</b>
		G1/4	G1/8	<a href="#">1862 13 10</a>	17	20.5	0.024
		G3/8	G1/8	<a href="#">1862 17 10</a>	22	21	0.043
			G1/4	<a href="#">1862 17 13</a>	22	24.5	0.049
		G1/2	G1/4	<a href="#">1862 21 13</a>	27	28.5	0.086
			G3/8	<a href="#">1862 21 17</a>	27	29	0.080
		G3/4	G1/2	<a href="#">1862 27 21</a>	32	39.5	0.144
		G1	G3/4	<a href="#">1862 34 27</a>	41	45	0.280

## 1864 Adaptor, Male NPT/Female BSPP Thread

	Stainless steel 316L 	<b>C1</b>	<b>C2</b>		<b>E</b>	<b>F</b>	<b>L</b>	<b>kg</b>
		NPT1/8	G1/8	<a href="#">1864 11 10</a>	7.5	14	21.5	0.015
		NPT1/4	G1/4	<a href="#">1864 14 13</a>	11	17	30	0.028
		NPT3/8	G3/8	<a href="#">1864 18 17</a>	11.5	22	31	0.043
		NPT1/2	G1/2	<a href="#">1864 22 21</a>	15	27	39.5	0.080

## 1867 Adaptor, Male BSPT/Female NPT Thread

	Stainless steel 316L 	<b>C1</b>	<b>C2</b>		<b>E</b>	<b>F</b>	<b>L</b>	<b>kg</b>
		R1/8	NPT1/8	<a href="#">1867 10 11</a>	8	14	21	0.015
		R1/4	NPT1/4	<a href="#">1867 13 14</a>	11.5	17	28.5	0.028
		R3/8	NPT3/8	<a href="#">1867 17 18</a>	12	22	29.5	0.044
		R1/2	NPT1/2	<a href="#">1867 21 22</a>	15.5	27	37.5	0.083